



TOP VIEW




SIDE VIEW




SECTION A-A


BOTTOM VIEW





- Notes: (Unless Otherwise Specified)
- 1) BODY; PLASTIC, SEMICONDUCTOR GRADE
 - 2) LEAD FRAME: COPPER, C-194F/H
 - 3) LEAD FRAME PLATING: Ni, Pd, Au
 - 4) FRAME THICKNESS: 0.203mm
 - 5) DIE PAD: 6.4 X 6.4mm
 - 6) JEDEC OUTLINE: MO-220




ISOMETRIC VIEW OF CAVITY SIDE



ISOMETRIC VIEW OF PCB SIDE

TOLERANCES UNLESS NOTED		APPROVALS	DATE	 www.MirrorSemi.com
X.X	± 0.05	DRAWN JMG	05/30/13	
X.XX	± 0.01	CHECKED		TITLE:
X.XXX	± 0.005	ENG APPR.		64-LEAD 8mm P=0.40mm QFN CAVITY PACKAGE
X.XXXX	± 0.0005	MFG APPR.		SCALE
ALL DIMENSIONS IN		Q.A.		SIZE
□ INCHES ✕ MILLIMETERS		CUST.		DWG. NO.
THIRD ANGLE PROJECTION		REVISED		446470
				M-QFN64W.4-G7
				8:1
				A
				DO NOT SCALE DRAWING
				SHEET 1 OF 4


TOP VIEW



SIDE VIEW
(BEFORE LID ATTACH)



BOTTOM VIEW




www.MirrorSemi.com

TITLE:
64-LEAD 8mm P=0.40mm
QFN CAVITY PACKAGE
LEAD NUMBERING

SCALE 8:1	SIZE A	DWG. NO. 446470 M-QFN64W.4-G7	REV A
---------------------	------------------	-------------------------------------	-----------------



BOND DIAGRAM



www.MirrorSemi.com

TITLE:
64-LEAD 8mm P=0.40mm
QFN CAVITY PACKAGE
BOND DIAGRAM

SCALE	SIZE	DWG. NO.	REV
10:1	A	446470 M-QFN64W.4-G7	A



DETAIL A
SCALE 40 : 1

Notes: (Unless Otherwise Specified).

1. DIMENSIONS ARE PRESENTED ONLY AS A GUIDELINE. DESIGNERS SHOULD USE THEIR OWN KNOWLEDGE BASE WHEN DESIGNING THE PCB.
2. SURROUND EACH SIDE OF I/O PERIMETER PADS WITH 0.060~0.075 mm (2.4~3.0mils) NSMD SOLDER MASK OPENING. OPTIONALLY OK TO USE RECTANGLE (NSMD) MASK OPENING AROUND I/O PADS.
3. ROUNDED PCB LAND PADS REDUCE SOLDER BRIDGING. PAD CHAMFER ANGLE MAY VARY.
4. PCB LANDS SHOULD BE 0.2mm LONGER THAN THE PACKAGE I/O PADS.
5. THE WIDTH OF PERIMETER PCB PADS SHOULD MATCH (1:1) THE WIDTH OF THE PACKAGE PADS.
6. REFER TO INDUSTRY REFERENCES SUCH AS IPC-SM-782 FOR PCB LAND PATTERN DESIGN.
7. THERMAL GROUND PADS MAY BE CHANGED TO SUITE REQUIREMENTS OF THE DESIGNER.
 - A. MAKE COPPER THERMAL PAD AS LARGE AS POSSIBLE.
 - B. DRILL MULTIPLE THERMAL VIAS 0.25~0.33mm DIAMETER USING 0.8~1.2mm PITCH GRID.
 - C. PLATE THERMAL VIA BARRELS WITH 1-OUNCE COPPER (18µm).
 - D. TENT (COVER) THERMAL VIAS WITH SOLDER MASK 0.1mm LARGER THAN THE VIA DIAMETER.
8. STENCIL DESIGN MAY BE CHANGED TO SUITE REQUIREMENTS OF THE DESIGNER.
 - A. LASER CUT STENCIL 0.125mm (5mil) THICK. APERTURE SIZE-TO-LAND RATIO OF 1:1.
 - B. THE SOLDER PASTE OPENING IN THE THERMAL PAD AREA SHOULD BE A MATRIX ARRAY OF SMALLER APERTURES INSTEAD OF ONE LARGE APERTURE TO CONTROL PASTE AMOUNTS.
 - C. APPLY 50% TO 80% SOLDER PASTE COVERAGE IN THE PAD AREA.

		www.MirrorSemi.com	
TITLE: 64-LEAD 8mm P=0.40mm QFN CAVITY PACKAGE RECOMMENDED PCB LAYOUT			
SCALE	SIZE	DWG. NO.	REV
8:1	A	446470 M-QFN64W.4-G7	A
DO NOT SCALE DRAWING			SHEET 4 OF 4